

DYNAMIC ENGINEERING

435 Park Dr., Ben Lomond, Calif. 95005

831-336-8891 Fax 831-336-3840

<http://www.dyneng.com>

sales@dyneng.com

Est. 1988

PB30seh

Driver Documentation

Win32 Driver Model

Revision A

Corresponding Hardware: Revision B

10-2005-0202

Corresponding Firmware: Revision B

PB30seh
WDM Device Driver for the
PMC-BiSerial3-0seh
PMC based Serial Interface

Dynamic Engineering
435 Park Drive
Ben Lomond, CA 95005
831-336-8891
831-336-3840 FAX

©2006 by Dynamic Engineering.
Other trademarks and registered trademarks are owned by their
respective manufactures.
Manual Revision A. Revised September 26, 2006

This document contains information of proprietary interest to Dynamic Engineering. It has been supplied in confidence and the recipient, by accepting this material, agrees that the subject matter will not be copied or reproduced, in whole or in part, nor its contents revealed in any manner or to any person except to meet the purpose for which it was delivered.

Dynamic Engineering has made every effort to ensure that this manual is accurate and complete. Still, the company reserves the right to make improvements or changes in the product described in this document at any time and without notice. Furthermore, Dynamic Engineering assumes no liability arising out of the application or use of the device described herein.

The electronic equipment described herein generates, uses, and can radiate radio frequency energy. Operation of this equipment in a residential area is likely to cause radio interference, in which case the user, at his own expense, will be required to take whatever measures may be required to correct the interference.

Dynamic Engineering's products are not authorized for use as critical components in life support devices or systems without the express written approval of the president of Dynamic Engineering.

Connection of incompatible hardware is likely to cause serious damage.



Table of Contents

Introduction	4
Note	4
Driver Installation	5
Windows 2000 Installation	5
Windows XP Installation	5
Driver Startup	6
IO Controls	9
IOCTL_PB3_OSEH_GET_INFO	9
IOCTL_PB3_OSEH_LOAD_PLL_DATA	9
IOCTL_PB3_OSEH_READ_PLL_DATA	9
IOCTL_PB3_OSEH_SET_BASE_CONFIG	9
IOCTL_PB3_OSEH_GET_BASE_CONFIG	10
IOCTL_PB3_OSEH_GET_STATUS	10
IOCTL_PB3_OSEH_START_TX	10
IOCTL_PB3_OSEH_STOP_TX	10
IOCTL_PB3_OSEH_START_RX	11
IOCTL_PB3_OSEH_STOP_RX	11
IOCTL_PB3_OSEH_SET_FIFO_LEVELS	11
IOCTL_PB3_OSEH_GET_FIFO_LEVELS	11
IOCTL_PB3_OSEH_GET_FIFO_COUNTS	12
IOCTL_PB3_OSEH_RESET_FIFOS	12
IOCTL_PB3_OSEH_WRITE_FIFO	12
IOCTL_PB3_OSEH_READ_FIFO	12
IOCTL_PB3_OSEH_REGISTER_EVENT	13
IOCTL_PB3_OSEH_ENABLE_INTERRUPTS	13
IOCTL_PB3_OSEH_DISABLE_INTERRUPTS	13
IOCTL_PB3_OSEH_FORCE_INTERRUPT	13
IOCTL_PB3_OSEH_GET_ISR_STATUS	14
Write	15
Read	15
Warranty and Repair	15
Service Policy	16
For Service Contact:	16



Introduction

The PB30seh driver is a Win32 driver model (WDM) device driver for the PMC-BiSerial3-OSEH from Dynamic Engineering. The PMC-BiSerial3-OSEH has a Spartan3-1500 Xilinx FPGA to implement the PCI interface, FIFOs and protocol control and status for one serial channel in and one serial channel out. Each channel uses three RS-485 signals: clock, serial data and reference clock. There is a programmable PLL with two clock outputs. One drives the internal clock reference for the transmit state machine, the other is output on IO line 18 to be connected to IO line 2 to simulate the external clock reference. There are two 4k x 32-bit data FIFOs, one for the transmit data and one for the receive data.

When the PMC-BiSerial3-OSEH is recognized by the PCI bus configuration utility it will start the PB30seh driver to allow communication with the device. IO Control calls (IOCTLs) are used to configure the board and read status. Read and Write calls are used to move blocks of data in and out of the device.

Note

This documentation will provide information about all calls made to the driver, and how the driver interacts with the device for each of these calls. For more detailed information on the hardware implementation, refer to the PMC-BiSerial3-OSEH user manual (also referred to as the hardware manual).



Driver Installation

There are several files provided in each driver package. These files include PB30seh.sys, PB30seh.inf, DDPB30seh.h, PB30sehGUID.h, PB30sehTest.exe, and PB30sehTest source files.

Windows 2000 Installation

Copy PB30seh.inf and PB30seh.sys to a floppy disk, or CD if preferred.

With the PMC-BiSerial3-OSEH hardware installed, power-on the PCI host computer and wait for the *Found New Hardware Wizard* dialogue window to appear.

- Select *Next*.
- Select *Search for a suitable driver for my device*.
- Select *Next*.
- Insert the disk prepared above in the desired drive.
- Select the appropriate drive e.g. *Floppy disk drives*.
- Select *Next*.
- The wizard should find the PB30seh.inf file.
- Select *Next*.
- Select *Finish* to close the *Found New Hardware Wizard*.

Windows XP Installation

Copy PB30seh.inf and PB30seh.sys to a floppy disk, or CD if preferred.

With the PMC-BiSerial3-OSEH hardware installed, power-on the PCI host computer and wait for the *Found New Hardware Wizard* dialogue window to appear.

- Insert the disk prepared above in the desired drive.
- Select *No when asked to connect to Windows Update*.
- Select *Next*.
- Select *Install the software automatically*.
- Select *Next*.
- Select *Finish* to close the *Found New Hardware Wizard*.

The DDPB30seh.h file is a C header file that defines the Application Program Interface (API) to the driver and contains the relevant bit defines for the PMC-BiSerial3-OSEH. The PB30sehGUID.h file is a C header file that defines the device interface identifier for the PB30seh driver. These files are required at compile time by any application that wishes to interface with the PB30seh driver. They



are not needed for driver installation.

The PB30sehTest.exe file is a sample Win32 console application that makes calls into the PB30seh driver to test each driver call without actually writing any application code. It is not required during the driver installation.

To use the PB30sehTest.exe program, open a command prompt console window and type a command in the form *PB30sehTest -dn -im* where *n* and *m* are the device number and driver ioctl number respectively. Type *PB30sehTest -dO -?* to display a list of commands and parameters (the PB30sehTest.exe file must be in the directory that the window is referencing). This application is intended to test the proper functioning of the individual driver calls, not for normal operation.

Driver Startup

Once the driver has been installed it will start automatically when the system recognizes the hardware. The devices are numbered in the order they are enumerated by the system starting with device 0. The interface to the device is identified using the globally unique identifier (GUID), which is defined in PB30sehGUID.h.

A handle can be opened to a specific board by using the CreateFile() function call and passing in the device name obtained from the system for the specified device number.

Below is example code for opening a handle for device *devNum*.

```
// The maximum length of the device name for a given interface
#define MAX_DEVICE_NAME 256
// Handle to the device object
HANDLE hPB30seh = INVALID_HANDLE_VALUE;
// Return status from command
LONG status;
// Handle to device interface information structure
HDEVINFO hDeviceInfo;
// The actual symbolic link name to use in the createfile
CHAR deviceName[MAX_DEVICE_NAME];
// Size of buffer required to get the symbolic link name
DWORD requiredSize;
// Interface data structures for this device
SP_DEVICE_INTERFACE_DATA interfaceData;
PSP_DEVICE_INTERFACE_DETAIL_DATA pDeviceDetail;

hDeviceInfo = SetupDiGetClassDevs(
    (LPGUID)&GUID_DEVINTERFACE_PB3_OSEH,
    NULL,
    NULL,
    DIGCF_PRESENT | DIGCF_DEVICEINTERFACE);
```



```

if(hDeviceInfo == INVALID_HANDLE_VALUE)
{
    printf("***Error: couldn't get class info, (%d)\n", GetLastError());
    exit(-1);
}

interfaceData.cbSize = sizeof(interfaceData);

// Find the interface for device devNum
if(!SetupDiEnumDeviceInterfaces(hDeviceInfo,
                                NULL,
                                (LPGUID)&GUID_DEVINTERFACE_PB3_OSEH,
                                devNum,
                                &interfaceData))
{
    status = GetLastError();
    if(status == ERROR_NO_MORE_ITEMS)
    {
        printf("***Error: couldn't find device(no more items), (%d)\n", devNum);
        SetupDiDestroyDeviceInfoList(hDeviceInfo);
        exit(-1);
    }
    else
    {
        printf("***Error: couldn't enum device, (%d)\n", status);
        SetupDiDestroyDeviceInfoList(hDeviceInfo);
        exit(-1);
    }
}

// Get the details data to obtain the symbolic link name
// First determine how much memory to allocate for the structure
if(!SetupDiGetDeviceInterfaceDetail(hDeviceInfo,
                                    &interfaceData,
                                    NULL,
                                    0,
                                    &requiredSize,
                                    NULL))
{
    if(GetLastError() != ERROR_INSUFFICIENT_BUFFER)
    {
        printf("***Error: couldn't get interface detail, (%d)\n",
              GetLastError());

        SetupDiDestroyDeviceInfoList(hDeviceInfo);
        exit(-1);
    }
}

// Allocate a buffer to get detail
pDeviceDetail = (PSP_DEVICE_INTERFACE_DETAIL_DATA)malloc(requiredSize);

if(pDeviceDetail == NULL)
{
    printf("***Error: couldn't allocate interface detail\n");
    SetupDiDestroyDeviceInfoList(hDeviceInfo);
    exit(-1);
}

```



```

pDeviceDetail->cbSize = sizeof(SP_DEVICE_INTERFACE_DETAIL_DATA);
// Get the detail info
if(!SetupDiGetDeviceInterfaceDetail(hDeviceInfo,
                                     &interfaceData,
                                     pDeviceDetail,
                                     requiredSize,
                                     NULL,
                                     NULL))
{
    printf("***Error: couldn't get interface detail(2), (%d)\n",
           GetLastError());

    SetupDiDestroyDeviceInfoList(hDeviceInfo);
    free(pDeviceDetail);
    exit(-1);
}

// Save the name
lstrcpy(deviceName,
        pDeviceDetail->DevicePath,
        MAX_DEVICE_NAME);

// Cleanup search
free(pDeviceDetail);
SetupDiDestroyDeviceInfoList(hDeviceInfo);

// Open driver and create the handle to the device
hPB30seh = CreateFile(deviceName,
                     GENERIC_READ   | GENERIC_WRITE,
                     FILE_SHARE_READ | FILE_SHARE_WRITE,
                     NULL,
                     OPEN_EXISTING,
                     NULL,
                     NULL);

if(hPB30seh == INVALID_HANDLE_VALUE)
{
    printf("***Error: couldn't open %s, (%d)\n",
           deviceName,
           GetLastError());
    exit(-1);
}

```



IO Controls

The driver uses IO Control calls (IOCTLs) to configure the device. IOCTLs refer to a single Device Object which controls a single board. IOCTLs are called using the Win32 function DeviceIoControl(), and passing in the handle to the device opened with CreateFile(). IOCTLs generally have input parameters, output parameters, or both. Often a custom structure is used. The IOCTLs defined in this driver are as follows:

IOCTL_PB3_OSEH_GET_INFO

Function: Returns the Driver version, Xilinx revision, PLL device ID, Switch value and Instance number.

Input: None

Output: PB3_OSEH_DRIVER_DEVICE_INFO structure

Notes: Switch value is the configuration of the onboard dipswitch that has been selected by the User (see the board silk screen for bit position and polarity). See DDPB30seh.h for the definition of PB3_OSEH_DRIVER_DEVICE_INFO.

IOCTL_PB3_OSEH_LOAD_PLL_DATA

Function: Loads the internal registers of the PLL.

Input: PB3_OSEH_PLL_DATA structure

Output: None

Notes: The PB3_OSEH_PLL_DATA structure has only one field: Data – an array of 40 bytes containing the data to write.

IOCTL_PB3_OSEH_READ_PLL_DATA

Function: Returns the contents of the PLL's internal registers.

Input: None

Output: PB3_OSEH_PLL_DATA structure

Notes: The register data is output in the PB3_OSEH_PLL_DATA structure in an array of 40 bytes.

IOCTL_PB3_OSEH_SET_BASE_CONFIG

Function: Writes to the base configuration register on the PMC-BiSerial3-Oseh.

Input: Value of control register (unsigned long integer)

Output: None

Notes: Only the bits in the BASE_CONFIG_MASK are controlled by this command. See the bit definitions in DDPB30seh.h for information on determining this value.



IOCTL_PB3_OSEH_GET_BASE_CONFIG

Function: Returns the configuration of the base control register.

Input: None

Output: Value of control register (unsigned long integer)

Notes: The return value includes the bits in BASE_CONFIG_MASK, the TX and RX enables, the DMA enables and BASE_MASTER_INT_EN.

IOCTL_PB3_OSEH_GET_STATUS

Function: Returns the status register value and clears the latched status bits.

Input: None

Output: Value of status register (unsigned long integer)

Notes: Returns FIFO, IO and interrupt status. If any of the latched bits are set, this call will explicitly clear only those bits. See the bit definitions in DDPB30seh.h for information on interpreting this value.

IOCTL_PB3_OSEH_START_TX

Function: Enables the transmit state-machine to start sending data.

Input: None

Output: None

Notes: If the transmit FIFO already has data in it, this command will start the serial data transmission. If the FIFO is empty, the transmit state-machine will wait for data to be written to the FIFO. As soon as the first data-word is written the transmission will begin. If the BASE_TX_CLR_DISABLE bit in the base control register is not set, the transmit enable will automatically clear when the FIFO data is exhausted. If this bit is set, the transmission will pause, waiting for more data to be written into the FIFO.

IOCTL_PB3_OSEH_STOP_TX

Function: Disables the transmit state-machine.

Input: None

Output: None

Notes: Use this call to disable the serial data transmission.



IOCTL_PB3_OSEH_START_RX

Function: Enables the receive state-machine to start receiving data.

Input: None

Output: None

Notes: When the receiver is enabled, a serial data bit is received for each low to high clock transition. When 32 bits have been received the data-word is written to the receive FIFO and the process continues until the receiver is disabled.

IOCTL_PB3_OSEH_STOP_RX

Function: Disables the receive state-machine.

Input: None

Output: None

Notes: Use this call when data reception is no longer desired.

IOCTL_PB3_OSEH_SET_FIFO_LEVELS

Function: Sets the transmitter almost empty and receiver almost full FIFO levels.

Input: PB3_OSEH_FIFO_LEVELS structure

Output: None

Notes: The FIFO levels are used to determine at what data count the TX almost empty and RX almost full status bits are asserted. See DDPB30seh.h for the definition of PB3_OSEH_FIFO_LEVELS.

IOCTL_PB3_OSEH_GET_FIFO_LEVELS

Function: Returns the transmitter almost empty and receiver almost full levels.

Input: None

Output: PB3_OSEH_FIFO_LEVELS structure

Notes: Returns the current values for the transmit almost empty and receive almost full FIFO levels. See DDPB30seh.h for the definition of PB3_OSEH_FIFO_LEVELS.



IOCTL_PB3_OSEH_GET_FIFO_COUNTS

Function: Returns the number of data words in the transmit and receive FIFOs.

Input: None

Output: PB3_OSEH_FIFO_COUNTS structure

Notes: There is a four-deep pipeline on the output of the receive FIFO that is required for DMA processing. This means that if the receive FIFO count is not zero, there are actually four more 32-bit words than are indicated. If the count is zero, there may be zero to four words in the pipeline. The STATUS_RX_VALID status bit will be a one if there is valid data in the pipeline. Similarly, when the transmitter is enabled, the first word written to the transmit FIFO will be read to prepare for transmission. This reduces the transmit FIFO count by one.

IOCTL_PB3_OSEH_RESET_FIFOS

Function: Resets both FIFOs

Input: None

Output: None

Notes: Resets the TX and RX FIFOs.

IOCTL_PB3_OSEH_WRITE_FIFO

Function: Writes a data-word to the TX FIFO.

Input: FIFO word (unsigned long integer)

Output: None

Notes: This call and the following call are used to make single-word accesses to the FIFOs.

IOCTL_PB3_OSEH_READ_FIFO

Function: Returns a data word from the RX FIFO.

Input: None

Output: FIFO word (unsigned long integer)

Notes:



IOCTL_PB3_OSEH_REGISTER_EVENT

Function: Registers an event to be signaled when an interrupt occurs.

Input: Handle to the Event object

Output: none

Notes: The caller creates an event with CreateEvent() and supplies the handle returned from that call as the input to this IOCTL. The driver then obtains a system pointer to the event and signals the event when a user interrupt is serviced. The user interrupt service routine waits on this event, allowing it to respond to the interrupt. The DMA interrupts do not cause the event to be signaled unless they are explicitly enabled in the enable interrupts call.

IOCTL_PB3_OSEH_ENABLE_INTERRUPTS

Function: Enables the DMA and/or master interrupts.

Input: PB3_OSEH_INT_SELECT structure

Output: None

Notes: The PB3_OSEH_INT_SELECT structure has three BOOLEAN members. When WrDmaDoneInt is true and an event has been registered with the IOCTL_PB3_OSEH_REGISTER_EVENT call, the event will be signaled when a write DMA completes. Similarly, when RdDmaDoneInt is true, the event will be signaled upon the completion of a read DMA. This behavior will persist until explicitly disabled with the IOCTL_PB3_OSEH_DISABLE_INTERRUPTS call. MasterInt enables all the other interrupts (TX, RX, FIFO levels etc.). This bit is cleared in the interrupt service routine and must therefore be re-enabled using this call after each of these interrupts is serviced.

IOCTL_PB3_OSEH_DISABLE_INTERRUPTS

Function: Disables the DMA and/or master interrupt.

Input: PB3_OSEH_INT_SELECT structure

Output: None

Notes: This call is used when interrupt processing is no longer desired.

IOCTL_PB3_OSEH_FORCE_INTERRUPT

Function: Causes a system interrupt to occur.

Input: None

Output: None

Notes: Causes an interrupt to be asserted on the PCI bus as long as the master interrupt is enabled. This IOCTL is used for development, to test interrupt processing.



IOCTL_PB3_OSEH_GET_ISR_STATUS

Function: Returns the interrupt status read in the ISR from the last user interrupt.

Input: None

Output: Interrupt status value (unsigned long integer)

Notes: Returns the interrupt status that was read in the interrupt service routine of the last interrupt caused by one of the enabled interrupts.



Write

PMC-BiSerial3-OSEH DMA data is written to the device using the write command. Writes are executed using the Win32 function WriteFile() and passing in the handle to the device opened with CreateFile(), a pointer to a pre-allocated buffer containing the data to be written, an unsigned long integer that represents the size of that buffer in bytes, a pointer to an unsigned long integer to contain the number of bytes actually written, and a pointer to an optional Overlapped structure for performing asynchronous IO.

Read

PMC-BiSerial3-OSEH DMA data is read from the device using the read command. Reads are executed using the Win32 function ReadFile() and passing in the handle to the device opened with CreateFile(), a pointer to a pre-allocated buffer that will contain the data read, an unsigned long integer that represents the size of that buffer in bytes, a pointer to an unsigned long integer to contain the number of bytes actually read, and a pointer to an optional Overlapped structure for performing asynchronous IO.

Warranty and Repair

Dynamic Engineering warrants this product to be free from defects under normal use and service and in its original, unmodified condition, for a period of one year from the time of purchase. If the product is found to be defective within the terms of this warranty, Dynamic Engineering's sole responsibility shall be to repair, or at Dynamic Engineering's sole option to replace, the defective product.

Dynamic Engineering's warranty of and liability for defective products is limited to that set forth herein. Dynamic Engineering disclaims and excludes all other product warranties and product liability, expressed or implied, including but not limited to any implied warranties of merchandisability or fitness for a particular purpose or use, liability for negligence in manufacture or shipment of product, liability for injury to persons or property, or for any incidental or consequential damages.

Dynamic Engineering's products are not authorized for use as critical components in life support devices or systems without the express written approval of the president of Dynamic Engineering.



Service Policy

Before returning a product for repair, verify as well as possible that the driver is at fault. The driver has gone through extensive testing and in most cases it will be “cockpit error” rather than an error with the driver. When you are sure or at least willing to pay to have someone help then call the Customer Service Department and arrange to speak with an engineer. We will work with you to determine the cause of the issue. If the issue is one of a defective driver we will correct the problem and provide an updated module(s) to you [no cost]. If the issue is of the customer’s making [anything that is not the driver] the engineering time will be invoiced to the customer. Pre-approval may be required in some cases depending on the customer’s invoicing policy.

Out of Warranty Repairs

Out of warranty support will be billed. The current minimum repair charge is \$125. An open PO will be required.

For Service Contact:

Customer Service Department
Dynamic Engineering
435 Park Dr.
Ben Lomond, CA 95005
831-336-8891
831-336-3840 fax

support@dyneng.com

All information provided is Copyright Dynamic Engineering.

